

No. 3, Industrial 2nd Rd., Ping-Chen Industrial District, Taoyuan, 324, Taiwan, R.O.C. TEL: 886-3-4690038 FAX: 886-3-4697532

E-mail: tstsales@mail.taisaw.com Web: www.taisaw.com

# **Product Specifications Approval Sheet**

Pro	duct Description: SAV	W Resonator 303.8	25 MHz SMD 3.0×3.0n	nm
TS	T Parts No.:TC0548A			
Cu	stomer Parts No.:			
	Customer signature requ	iired		
	Company:			
	Division:			
	Approved by :			
	Date:			
			Hong Pu Lin	
Checked by:		Hongpu Lin	7.00,00	
Approval by:		Andy Yu	Hong Pu Lin Andy Yn	
Da	te:	2019/04/25		

- 1. Customer signed back is required before TST can proceed with sample build and receive orders.
- 2. Orders received without customer signed back will be regarded as agreement on the specifications.
- 3. Any specifications changes must be approved upon by both parties and a new revision of specifications shall be released to reflect the changes



# TAI-SAW TECHNOLOGY CO., LTD. No. 3, Industrial 2nd Rd., Ping-Chen Industrial District, Taoyuan, 324, Taiwan, R.O.C.

TEL: 886-3-4690038 FAX: 886-3-4697532 E-mail: tstsales@mail.taisaw.com Web: www.taisaw.com

#### SAW Resonator 303.825 MHz

MODEL NO.: TC0548A **REV. 2.0** 

#### **A.FEATURES:**

1. 1-Port Resonator.

#### **B. MAXIMUM RATING:**

1. Input Power Level: 0 dBm

2. DC Voltage: 5 V

3. Operating Temperature:-40 °C to +85 °C

4. Storage Temperature: -40 °C to +85 °C

5. Moisture Sensitive Level (MSL): Level 1

**RoHS Compliant** Lead free Lead-free soldering

#### C. ELECTRICAL CHARACTERISTICS:


Reference Temperature T<sub>A</sub>=25°C

Characteristic	Units	Minimum	Typical	Maximum
Center frequency Fc	MHz	303.750	303.825	303.900
Insertion Loss IL	dB	-	1.3	1.8
Unload quality factor Qu		10000	17300	-
Ageing of fc	ppm/yr	-	ı	±10
Motional capacitance C1	fF	-	2.05	-
Motional inductance L1	$\mu$ H	-	135.9	-
Motional resistance R1	Ohm	-	14.97	-
Parallel capacitance Co	pF	-	3.88	-
Frequency Temperature coefficient (TC <sub>f</sub> )	ppm/c*2	-	0.032	-
Turnover To	deg.C	-5	10	25
Package size		SMD 3.0X3.0X1.4 mm		

Temperature dependence of fc:  $fc(T_A)=fc(T_O)(1-TC_f(T_A-T_O)^2)$ 

#### **D.EQUVIRENT CIRCUIT:**


One-Port Resonator:



TAI-SAW TECHNOLOGY CO., LTD.

TST DCC Release document

#### **E.OUTLINEDRAWING:**



Date code: Provided by planer each year

Year code: 9 for 2009,0 for 2010, 1 for 2011...

#### F.FREUENCY CHARACTERISTICS:




TAI-SAW TECHNOLOGY CO., LTD.


**TST DCC**Release document

# G.TEST CIRCUIT:

#### Network analyzer




# H.PCB FOOTPRINT:




# I.PACKING:

#### 1. REEL DIMENSION



#### 2. TAPE DIMENSION



#### J. RECOMMENDED REFLOW PROFILE:

- 1. Preheating shall be fixed at  $150\sim180^{\circ}$ C for  $60\sim90$  seconds.
- 2. Ascending time to preheating temperature 150°C shall be 30 seconds min.
- 3. Heating shall be fixed at 220°C for 50~80 seconds and at 260°C+0/-5°C peak (20~40sec).
- 4. Time: 2 times.

